



Deposited via The University of Sheffield.

White Rose Research Online URL for this paper:

<https://eprints.whiterose.ac.uk/id/eprint/78118/>

Monograph:

Banks, S.P. and Chanane, B. (1989) A Functional Expansion and Stability for Nonlinear Input-Output Maps. Research Report. Acse Report 359 . Dept of Automatic Control and System Engineering. University of Sheffield

Reuse

Items deposited in White Rose Research Online are protected by copyright, with all rights reserved unless indicated otherwise. They may be downloaded and/or printed for private study, or other acts as permitted by national copyright laws. The publisher or other rights holders may allow further reproduction and re-use of the full text version. This is indicated by the licence information on the White Rose Research Online record for the item.

Takedown

If you consider content in White Rose Research Online to be in breach of UK law, please notify us by emailing eprints@whiterose.ac.uk including the URL of the record and the reason for the withdrawal request.

PAM Q 629.8 (S)

A Functional Expansion And Stability PAM BOX

For

Nonlinear Input-Output Maps

by

S. P. Banks and B. Chanane

Department Of Control Engineering

University Of Sheffield

Mappin Street

SHEFFIELD, S1 3JD

Research Report No359

April 1989

Abstract

In this paper we shall use the global bilinearization of a linear analytic system using the tensor operator approach introduced in [6]. We shall generalize the result on finite dimensional bilinear systems [13] to this class of systems. We use the idea of diagonal dominance for tensor operators to derive an exponential stability result. Few examples will be presented to illustrate the theory.

200091832



1 Introduction and Notation:

Since its use by Brockett [9], the Carleman linearization [12] has been successfully applied and extended by Lo [18], Brockett [10], Krener [17], Takata [19] and Banks and his co-workers [1]–[8]. It has been always seen as a promising technique to tackle general nonlinear systems.

In this paper we shall apply this technique to transform linear analytic systems into bilinear ones in the space of tensors [16]. Then we expand the results in [13] to this class of systems. We shall present a new functional expansion of the given input-output map and derive a sufficient condition for exponential stability. This condition turns out to be the intuitively appealing result that one of the tensor operators involved verifies the ‘diagonal dominance’ property to be precised later. The paper is organised as follows. In section 2 we shall present the global exponential stability for free nonlinear systems. In section 3 we present the new input-output expansion from which we deduce in section 4 some stability results; these constitute the generalization of the results in [13]. Finally, in section 5, few examples will be presented to illustrate the theory.

We shall use the same notations as in [6], that is an n -multi-index is an n -multiple $\mathbf{i} = (i_1, \dots, i_n)$ of non-negative integers; its length (or order) is given by $|\mathbf{i}| = i_1 + \dots + i_n$. The sum of two multi-indices \mathbf{i} and \mathbf{j} is defined as $\mathbf{i} + \mathbf{j} = (i_1 + j_1, \dots, i_n + j_n)$. We say that $\mathbf{i} \leq \mathbf{j}$ if $i_k \leq j_k$ for $k = 1, \dots, n$. When $\mathbf{i} \leq \mathbf{j}$, we define $\mathbf{j} - \mathbf{i}$ as $(j_1 - i_1, \dots, j_n - i_n)$. We also define $\mathbf{i}! = i_1! \dots i_n!$ and

$$\mathbf{x}^{\mathbf{i}} = x_1^{i_1} \dots x_n^{i_n}$$

for $\mathbf{x} = (x_1, \dots, x_n) \in \mathbb{R}^n$. Also, $\mathbf{1}(r)$ will denote the n -multi-index with 1 in the r th place and zero elsewhere, and

$$\delta_{\mathbf{i}}^{\mathbf{j}} = \begin{cases} 1 & \text{if } \mathbf{i} = \mathbf{j}, \\ 0 & \text{if } \mathbf{i} \neq \mathbf{j}. \end{cases}$$

We write $\mathbf{i} \geq \mathbf{0}$ if and only if $i_1 \geq 0, \dots, i_n \geq 0$.

For an analytic function $h : \mathbb{R}^n \rightarrow \mathbb{R}$, Taylor's formula becomes

$$h(\mathbf{x}) = \sum_{\mathbf{i} \geq \mathbf{0}} \frac{\mathbf{x}^{\mathbf{i}}}{\mathbf{i}!} h^{(\mathbf{i})}(\mathbf{0}),$$

where

$$h^{(\mathbf{i})}(\mathbf{x}) = \partial^{|\mathbf{i}|} h(\mathbf{x}) / \partial x_1^{i_1} \dots \partial x_n^{i_n},$$

Let l^2 denote the standard Banach space of square summable sequences and let l_e^2 [5] denote the Banach space of sequences $(\alpha_n)_{n \geq 0}$ such that the sequence $(\alpha_n/n!)_{n \geq 0}$ belongs to l^2 . Define a norm on l_e^2 by

$$\|(\alpha_n)_{n \geq 0}\|_e = \left(\sum_{n \geq 0} \frac{\alpha_n^2}{(n!)^2} \right)^{\frac{1}{2}} \text{ for } (\alpha_n)_{n \geq 0} \in l_e^2.$$

Now consider the algebraic tensor product $\mathcal{L}_n = \otimes_n l_e^2$ and let $\|\cdot\|$ be any cross norm on \mathcal{L}_n [20]. For a simple tensor Φ , we have

$$\Phi = (\phi_{i_1 \dots i_n}) = (\alpha_{i_1}^1 \dots \alpha_{i_n}^n) = \alpha^1 \otimes \dots \otimes \alpha^n,$$

where $\alpha^k = (\alpha_{i_k}^k)_{i_k \geq 0} \in l_e^2 (k = 1, \dots, n)$. Then

$$\|\Phi\| = \prod_{k=1}^n \|\alpha^k\|_e,$$

For $\Phi = (\phi_{\mathbf{i}})_{\mathbf{i} \geq \mathbf{0}}$ in the space of tensors \mathcal{L}_n^T of the form $\Phi = (\mathbf{x}^{\mathbf{i}})_{\mathbf{i} \geq \mathbf{0}}$, we have,

$$\begin{aligned} \|\Phi\| &= \prod_{k=1}^n \|(\alpha_k^{i_k})_{i_k \geq 0}\|_e \\ &= \prod_{k=1}^n \left(\sum_{i_k \geq 0} \frac{1}{(i_k!)^2} x_k^{2i_k} \right)^{\frac{1}{2}} \\ &= \left(\sum_{\mathbf{i} \geq \mathbf{0}} \frac{1}{(\mathbf{i}!)^2} \phi_{\mathbf{i}}^2 \right)^{\frac{1}{2}} \end{aligned} \quad (1.1)$$

Let A be a tensor operator defined by $(A\Phi)_{\mathbf{q}} = \sum_{\mathbf{p} \geq \mathbf{0}} a_{\mathbf{q}}^{\mathbf{p}} \phi_{\mathbf{p}}$, \mathbf{p} and \mathbf{q} being multi-indices. We say that A satisfies the 'diagonal dominance' property if there exists a $\rho > 0$ such that $a_{\mathbf{p}}^{\mathbf{p}} + \sum_{\mathbf{l} \neq \mathbf{p}} |a_{\mathbf{l}}^{\mathbf{p}}| < -\rho, \forall \mathbf{p} \geq \mathbf{0}$. This is a byproduct of the generalization of Gersgorin's theorem to tensor operators [4].

2 Global exponential stability for free nonlinear systems:

Consider the system without input given by

$$\dot{\mathbf{x}} = f(\mathbf{x}) \quad , \quad \mathbf{x}(0) = \mathbf{x}_0 \quad (2.1)$$

where $\mathbf{x}_0 \in \mathbb{R}^n$ and $f : \mathbb{R}^n \rightarrow \mathbb{R}^n$ is an analytic function such that $f(0) = 0$.

We shall assume that the solution exists for all time.

Differentiating $\phi_{\mathbf{p}} = \mathbf{x}^{\mathbf{p}}$, where \mathbf{p} is an n -multi-index, along the trajectories of (2.1), we obtain

$$\begin{aligned} \dot{\phi}_{\mathbf{p}} &= \sum_{k=1}^n p_k \mathbf{x}^{\mathbf{p}-1(\mathbf{k})} \dot{x}_k \\ &= \sum_{k=1}^n p_k \mathbf{x}^{\mathbf{p}-1(\mathbf{k})} \left(\sum_{|\mathbf{m}|>0} f_k^{\mathbf{m}} \mathbf{x}^{\mathbf{m}} \right) \\ &= \sum_{|\mathbf{m}|>0} \sum_{k=1}^n p_k f_k^{\mathbf{m}} \mathbf{x}^{\mathbf{p}+\mathbf{m}-1(\mathbf{k})} \\ &= \sum_{|\mathbf{l}|>0} a_{\mathbf{p}}^{\mathbf{l}} \phi_{\mathbf{p}} \end{aligned} \quad (2.2)$$

where

$$a_{\mathbf{p}}^{\mathbf{l}} = \sum_{k=1}^n p_k f_k^{\mathbf{l}-\mathbf{p}+1(\mathbf{k})} \quad (2.3)$$

or in compact form

$$\dot{\Phi} = A\Phi \quad , \quad \Phi(0) = \Phi^0 \quad (2.4)$$

so

$$\dot{\phi}_{\mathbf{p}} = a_{\mathbf{p}}^{\mathbf{p}} \phi_{\mathbf{p}} + \sum_{\mathbf{l} \neq \mathbf{p}} a_{\mathbf{p}}^{\mathbf{l}} \phi_{\mathbf{l}} \quad (2.5)$$

hence

$$\frac{d}{dt} [e^{-a_{\mathbf{p}}^{\mathbf{p}} t} \phi_{\mathbf{p}}] = e^{-a_{\mathbf{p}}^{\mathbf{p}} t} \sum_{\mathbf{l} \neq \mathbf{p}} a_{\mathbf{p}}^{\mathbf{l}} \phi_{\mathbf{l}} \quad (2.6)$$

and

$$e^{-a_{\mathbf{p}}^{\mathbf{p}} t} \phi_{\mathbf{p}}(t) = \phi_{\mathbf{p}}(0) + \int_0^t e^{-a_{\mathbf{p}}^{\mathbf{p}} \tau} \sum_{\mathbf{l} \neq \mathbf{p}} a_{\mathbf{p}}^{\mathbf{l}} \phi_{\mathbf{l}}(\tau) d\tau \quad (2.7)$$

which can be rewritten as

$$e^{-a_{\mathbf{p}}^{\mathbf{p}}t} \phi_{\mathbf{p}}(t) = \phi_{\mathbf{p}}(0) + \int_0^t e^{-a_{\mathbf{p}}^{\mathbf{p}}\tau} \phi_{\mathbf{p}}(\tau) \sum_{\mathbf{l} \neq \mathbf{p}} a_{\mathbf{l}}^{\mathbf{p}} \phi_{\mathbf{l}-\mathbf{p}}(\tau) d\tau \quad (2.8)$$

Suppose that $\mathbf{x}(\tau)$ is in the unit ball

$\{\mathbf{x} \in \mathbb{R}^n : \max_{k=1, \dots, n} |x_k| < 1\}$ for $\tau \leq t$, then,

$$|e^{-a_{\mathbf{p}}^{\mathbf{p}}t} \phi_{\mathbf{p}}(t)| \leq |\phi_{\mathbf{p}}(0)| + \int_0^t |e^{-a_{\mathbf{p}}^{\mathbf{p}}\tau} \phi_{\mathbf{p}}(\tau)| \sum_{\mathbf{l} \neq \mathbf{p}} |a_{\mathbf{l}}^{\mathbf{p}}| d\tau \quad (2.9)$$

Using Gronwall's lemma, we conclude

$$|e^{-a_{\mathbf{p}}^{\mathbf{p}}t} \phi_{\mathbf{p}}(t)| \leq |\phi_{\mathbf{p}}(0)| e^{t \sum_{\mathbf{l} \neq \mathbf{p}} |a_{\mathbf{l}}^{\mathbf{p}}|} \quad (2.10)$$

Thus,

$$\begin{aligned} |\phi_{\mathbf{p}}(t)| &\leq e^{(\sum_{\mathbf{l} \neq \mathbf{p}} |a_{\mathbf{l}}^{\mathbf{p}}| + a_{\mathbf{p}}^{\mathbf{p}})t} \\ &\leq e^{-\rho t} \end{aligned} \quad (2.11)$$

hence, taking into account (1.1), we obtain

$$\|\Phi(t)\| \leq e^{-\rho t} \quad (2.12)$$

and

$$\|e^{At}\| \leq e^{-\rho t} \quad (2.13)$$

(since $\|\Phi\| = \|e^{At} \Phi^0\| \leq e^{-\rho t}$, $\forall \Phi^0 = (\mathbf{x}_0^i)_{i \geq 0}$. Note that this inequality only holds on the nonlinear subspace \mathcal{L}_n^T of tensors of the form $\Phi = (\mathbf{x}^i)_{i \geq 0}$ and it does not follow that it holds for Φ^0 in the closed linear span of tensors of this form [3]) provided there exists a $\rho > 0$ such that

$$a_{\mathbf{p}}^{\mathbf{p}} + \sum_{\mathbf{l} \neq \mathbf{p}} |a_{\mathbf{l}}^{\mathbf{p}}| \leq -\rho < 0, \quad \forall \mathbf{p} \geq 0. \quad (2.14)$$

Hence, we have proved the following

Theorem 1:

Any solution of (2.1) starting in the unit ball $\{\mathbf{x} \in \mathbb{R}^n : \max_{k=1, \dots, n} |x_k| < 1\}$

will remain there and will go to zero exponentially as $t \rightarrow \infty$ if there exists $\rho > 0$ such that

$$a_p^p + \sum_{l \neq p} |a_l^p| \leq -\rho < 0 \quad , \quad \forall p \geq 0. \quad (2.15)$$

Remark 1:

This diagonal dominance property known as Gersgoring's theorem has been used in [4] to prove the non-existence of limit cycles in nonlinear systems.

Corollary 1:

Any solution of (2.1) starting in the unit ball $\{\mathbf{x} \in \mathbb{R}^n : \max_{k=1, \dots, n} |x_k| < 1\}$ will remain there and will go to zero exponentially as $t \rightarrow \infty$ if there exists $\rho > 0$ such that

$$f_k^{1(k)} + \sum_{q \geq 0} |f_k^{q+1(k)}| \leq -\rho \quad (2.16)$$

Proof:

Indeed,

$$\begin{aligned} a_p^p + \sum_{l \neq p} |a_l^p| &\leq \sum_{k=1}^n p_k f_k^{1(k)} + \sum_{l \neq p} \sum_{k=1}^n p_k |f_k^{1-p+1(k)}| \\ &= \sum_{k=1}^n p_k \left[f_k^{1(k)} + \sum_{l \neq p} |f_k^{1-p+1(k)}| \right] \\ &= \sum_{k=1}^n p_k \left[f_k^{1(k)} + \sum_{q \neq 0} |f_k^{q+1(k)}| \right] \end{aligned} \quad (2.17)$$

Therefore, if

$$f_k^{1(k)} + \sum_{q \neq 0} |f_k^{q+1(k)}| \leq -\rho \quad , \quad k = 1, \dots, n \quad (2.18)$$

then, the previous theorem applies.

3 A nonlinear input-output map for linear analytic systems:

Consider the linear analytic system

$$\begin{aligned}\dot{\mathbf{x}} &= f(\mathbf{x}) + \sum_{j=1}^m u_j g_j(\mathbf{x}) \quad , \quad \mathbf{x}(0) = x_0 \\ y &= h(\mathbf{x})\end{aligned}\quad (3.1)$$

where $x_0 \in \mathbb{R}^n$, $u_j \in \mathbb{R}$, $j = 1, \dots, m$ and $f, g_j (j = 1, \dots, m) : \mathbb{R}^n \rightarrow \mathbb{R}^n$ and $h : \mathbb{R}^n \rightarrow \mathbb{R}^r$ are analytic functions such that $f(0) = 0, g(0) = 0$. We shall assume that the solution exists for all time and (without loss of generality) that $\max_{k=1, \dots, n} |x_{0k}| \leq 1$.

Let $u_0(t) = 1 ; t \geq 0$ and $g_0 = f$, (3.1) becomes

$$\begin{aligned}\dot{\mathbf{x}} &= \sum_{j=0}^m u_j g_j(\mathbf{x}) \quad , \quad \mathbf{x}(0) = x_0 \\ y &= h(\mathbf{x})\end{aligned}\quad (3.2)$$

As in previous section, define $\phi_p = \mathbf{x}^p$ for an n -multi-index p , differentiating along the trajectories of (3.2) and replacing the g_j , ($j = 0, \dots, m$) by their Taylor series expansions, we obtain

$$\begin{aligned}\dot{\phi}_p &= \sum_{k=1}^n p_k \mathbf{x}^{p-1(k)} \dot{x}_k \\ &= \sum_{k=1}^n p_k \mathbf{x}^{p-1(k)} \sum_{j=0}^m u_j \sum_{|\mathbf{l}| \geq 0} g_{jk}^{\mathbf{l}} x^{\mathbf{l}} \\ &= \sum_{|\mathbf{l}| \geq 0} \sum_{k=1}^n p_k \sum_{j=0}^m u_j g_{jk}^{\mathbf{l}} \mathbf{x}^{p+1-\mathbf{l}(k)} \\ &= \sum_{j=0}^m u_j \sum_{|\mathbf{q}| \geq 0} \left[\sum_{k=1}^n p_k g_{jk}^{\mathbf{q}-p+1(k)} \right] \phi_{\mathbf{q}}\end{aligned}$$

That is

$$\dot{\Phi} = \sum_{j=0}^m u_j N_j \Phi \quad ; \quad \Phi(0) = \Phi^0 \quad (3.3)$$

$$y = C\Phi \quad (3.4)$$

where

$$\begin{aligned}\Phi &= (\phi_p)_p \\ (N_j \Phi)_p &= \sum_{|q| \geq 0} a_j^q(p) \phi_q \\ a_j^q(p) &= \sum_{k=1}^n p_k g_{jk}^{q-p+1(k)} \\ (C\Phi)_k &= \sum_{|q| \geq 0} h_k^q \phi_q\end{aligned}$$

Now, for a given k , consider the change of variable

$$\Psi = e^{-N_k \int_0^t u_k(\tau) d\tau} \Phi \quad (3.5)$$

We have $\Psi(0) = \Phi^0$. Differentiating Ψ and taking into account (3.3) we get

$$\dot{\Psi} = e^{-N_k \int_0^t u_k(\tau) d\tau} P_k(t) e^{N_k \int_0^t u_k(\tau) d\tau} \Psi \quad (3.6)$$

where, $P_k(t) = \sum_{j \neq k} u_j N_j$.

Let $U_k(\tau) = \int_0^\tau u_k(\sigma) d\sigma$, Then,

$$\Psi(t) = \Phi^0 + \int_0^t e^{-N_k U_k(\tau)} P_k(\tau) e^{N_k U_k(\tau)} \Psi(\tau) d\tau \quad (3.7)$$

Hence, we obtain the nonlinear input-output map given by

$$\begin{aligned}y(t) &= C e^{N_k U_k(t)} \Phi^0 + \\ &+ \sum_{l \geq 1} \sum_{j_1 \neq k} \cdots \sum_{j_l \neq k} \int_0^t \int_0^{\tau_1} \cdots \int_0^{\tau_{l-1}} \\ &C e^{N_k [U_k(t) - U_k(\tau_l)]} N_{j_l} e^{N_k [U_k(\tau_l) - U_k(\tau_{l-1})]} N_{j_{l-1}} \\ &\cdots N_{j_2} e^{N_k [U_k(\tau_2) - U_k(\tau_1)]} N_{j_1} e^{N_k U_k(\tau_1)} \Phi^0 \\ &u_{j_l}(\tau_l) \cdots u_{j_1}(\tau_1) d\tau_1 \cdots d\tau_l\end{aligned} \quad (3.8)$$

4 Stability of linear analytic systems:

In this section we shall present sufficient conditions for a kind of L^∞ -stability of nonlinear systems. In [13] we introduced the following

Definition 1:

We say that the nonlinear system (3.1) is $(\Omega, L^\infty[0, \infty; \mathbb{R}^p])$ -stable where $\Omega \subset L^\infty[0, \infty; \mathbb{R}^m]$ if

$$\forall u \in \Omega \subset L^\infty[0, \infty; \mathbb{R}^m] \longrightarrow y \in L^\infty[0, \infty; \mathbb{R}^p]$$

where u and y are respectively the input and output of the system.

We claim the following:

Theorem 2:

Suppose there exists at least one N_j ($j = 0, \dots, m$) (say N_k) verifying the diagonal dominance property,

If Ω is the set of $u \in L^\infty[0, \infty; \mathbb{R}^m]$ for which the following conditions hold:

(a) $\lim_{t \rightarrow \infty} \int_0^t [-\rho_k u_k(\tau) + \|P_k(\tau)\|] d\tau < \infty$

where $\rho_k > 0$ is such that $\|e^{N_k t}\| \leq e^{-\rho_k t}$, $P_k(t) = \sum_{j \neq k} u_j(t) N_j$

(b) $u_k \geq 0$.

Then the system (3.1) is $(\Omega, L^\infty[0, \infty; \mathbb{R}^p])$ -stable. Furthermore, if the limit is $-\infty$ then $y(t) \rightarrow 0$ as $t \rightarrow \infty$.

Proof:

From the previous section, we know that if N_k satisfies the diagonal dominance property, then there exists a positive constant $\rho_k > 0$ such that $\|e^{N_k t}\| \leq e^{-\rho_k t}$. Combining (3.5) and (3.3) we obtain

$$\Phi(t) = e^{N_k U_k(t)} \Phi_0 + \int_0^t e^{N_k [U_k(t) - U_k(\tau)]} P_k(\tau) \Phi(\tau) d\tau \quad (4.1)$$

which yields,

$$\|\Phi(t)\| \leq \|\Phi_0\| e^{-\rho_k U_k(t)} + \int_0^t e^{-\rho_k [U_k(t) - U_k(\tau)]} \|P_k(\tau)\| \|\Phi(\tau)\| d\tau \quad (4.2)$$

since $U_k(t) \geq U_k(\tau) \geq 0$ for $t \geq \tau \geq 0$ (because $u_k \geq 0$). Therefore,

$$e^{\rho_k U_k(t)} \|\Phi(t)\| \leq \|\Phi_0\| + \int_0^t \|P_k(\tau)\| e^{\rho_k U_k(\tau)} \|\Phi(\tau)\| d\tau \quad (4.3)$$

Using Gronwall's lemma, we obtain

$$e^{\rho_k U_k(t)} \|\Phi(t)\| \leq \|\Phi_0\| \exp\left[\int_0^t \|P_k(\tau)\| d\tau\right] \quad (4.4)$$

Hence,

$$\|y(t)\| \leq \|C\| \|\Phi_0\| \exp\int_0^t [-\rho_k u_k(\tau) + \|P_k(\tau)\|] d\tau \quad (4.5)$$

Thus the theorem is proved.

Corollary 2:

Assume that there exists at least one N_j ($j = 0, \dots, m$) (say N_k) satisfying the diagonal dominance property, and let Ω be the set of $u \in L^\infty[0, \infty; \mathbb{R}^m]$ for which

$$(a) \lim_{t \rightarrow \infty} \int_0^t [-\rho_k u_k(\tau) + \sum_{j \neq k} |u_j(\tau)| \|N_j\|] d\tau < \infty$$

where $\rho_k > 0$ is such that $\|e^{N_k t}\| \leq e^{-\rho_k t}$

and

$$(b) u_k \geq 0.$$

Then the system (3.1) is $(\Omega, L^\infty[0, \infty; \mathbb{R}^p])$ -stable. Furthermore, if the limit is $-\infty$ then $y(t) \rightarrow 0$ as $t \rightarrow \infty$.

5 Examples:

In this section we shall present few examples to illustrate the theory.

Example 1: All the solutions of the system

$$\begin{cases} \dot{x}_1 &= -5x_1 + 2x_1^3 x_2^2 - x_1^2 \\ \dot{x}_2 &= -2x_2 + x_1^4 \end{cases}$$

starting in the unit ball $\{(a, b) \in \mathbb{R}^2 / \max(|a|, |b|) \leq 1\}$ will go to zero exponentially as $t \rightarrow \infty$ and $|x_i(t)| \leq |x_i(0)| e^{-t}$, $i = 1, 2$. Indeed, the sum of a diagonal coefficient -5 (resp. -2) and the absolute values of the corresponding off-diagonal elements 2, 1 (resp. 1) is -2 (resp. -1).

Example 2: Consider the system

$$\begin{cases} \dot{x}_1 &= -5x_1 + \frac{1}{4}x_2^3x_1 \\ \dot{x}_2 &= -6x_1 - \frac{1}{8}x_1^2x_2^3 \end{cases}$$

such that $x_1(0) = x_{10}, x_2(0) = x_{20}$. Let $\alpha = \max\{|x_{10}|, |x_{20}|\} \neq 0$. Define $z = \frac{1}{\alpha}\mathbf{x}$. We obtain,

$$\begin{cases} \dot{z}_1 &= -5z_1 + \frac{\alpha^3}{4}z_2^3z_1 \\ \dot{z}_2 &= -6z_1 - \frac{\alpha^4}{8}z_1^2z_2^3 \end{cases}$$

A sufficient condition for exponential stability is given by the diagonal dominance inequalities from which we get $\alpha = \max\{|x_{10}|, |x_{20}|\} \leq 2(3)^{\frac{1}{4}}$.

Example 3: Consider the single-input system

$$\dot{\mathbf{x}} = f(\mathbf{x}) + ug(\mathbf{x}) \quad , \quad \mathbf{x}(0) = \mathbf{x}_0 \quad , \quad \mathbf{y} = \mathbf{x} \quad (5.1)$$

where $f(x_1, x_2) = (x_1 + x_2^2, -x_1^2 + 2x_2)^T$, $g(x_1, x_2) = (-2x_1 + x_1x_2, -3x_2 + x_1^2)^T$.

The tensor operator associated with g is diagonally dominant ($\rho = 1$). Let Ω be the set of $u \in L^\infty[0, \infty; \mathbb{R}^m]$ for which the following conditions hold:

(a) $\lim_{t \rightarrow \infty} \int_0^t [-u(\tau) + \|N_0\|] d\tau < \infty$, (b) $u \geq 0$. From theorem 1, the system is $(\Omega, L^\infty[0, \infty; \mathbb{R}])$ -stable, and if the limit is $-\infty$ then $y(t) \rightarrow 0$ as $t \rightarrow \infty$. N_0 is the tensor operator associated with f .

6 Conclusion:

We have presented in this paper a functional series representation for linear analytic systems using the tensor operator approach introduced in [6]. This result extends the one derived for bilinear systems [13]. We also derived a condition under which a free nonlinear system is globally exponentially stable. The condition is based on the diagonal dominance for tensor operators.

References

- [1] S. P. Banks, 1985, 'On the generation of infinite dimensional bilinear systems and Volterra series ' *Inter. J. Sys. Sci.* , 16 pp 145-160.
- [2] S. P. Banks, A. Ashtiani, 1985, 'Linear and bilinear infinite-dimensional representations of finite-dimensional nonlinear systems ', *Inter.J. Sys. Sci.* , pp. 841-853 .
- [3] S. P. Banks, 1986a, 'On the global bilinearization of nonlinear systems and the existence of Volterra series ', *Int. J. Cont.* .
- [4] S. P. Banks, 1986b, 'Tensor operators and limit cycles in non-linear systems ', *Int. J. Control*, Vol. 43, No. 3, pp. 883-890.
- [5] S. P. Banks, 1988, **Mathematical Theories Of Nonlinear Systems**, Prentice-Hall.
- [6] S. P. Banks, B. Chanane, 1988a, 'A generalized frequency response for non-linear systems ', *I.M.A. J. Of Math. Cont. & Inf.*, **5**, 147-166. 1988.
- [7] S. P. Banks and B. Chanane, 1988b, 'On frequency response for nonlinear systems ', to appear in the Conference Proceedings of the Fifth I.M.A. International Conference on Control Theory, University of Strathclyde, Glasgow, UK.
- [8] S. P. Banks, M. K. Yew, 1985, 'On a class of suboptimal controls for infinite dimensional bilinear systems', *Systems & Control Letters*, **5**, pp. 327-333.
- [9] R. W. Brockett, 1973, 'Lie algebras and Lie groups in control theory ', in D. Q. Mayne and R. W. Brockett Eds. **Geometric Methods in Systems Theory**, Reidel, Dordrecht.
- [10] R. W. Brockett, 1976, 'Volterra series and geometric control theory ' *Automatica*, **12** pp 167-176, (Addendum with E. Gilbert, Vol 12).

- [11] R. W. Brockett, 1977, 'Convergence of Volterra Series on Infinite Intervals and Bilinear Approximations' In **Nonlinear Systems and Applications**, V. Lakshmikanthan (Ed.) Academic Press.
- [12] T. Carleman, 1932, 'Application de la th'éorie des équations singulières aux équations différentielles de la dynamique', *T. Ark. Mat. Astron. Fys.*, **22B** (1).
- [13] B. Chanane, S. P. Banks, 1988a, 'Nonlinear Input-Output Maps For Bilinear Systems and Stability', submitted to *I.M.A. J. Of Math. Cont. & Inf.*
- [14] B. Chanane, S. P. Banks, 1988b, 'Realization and Generalized Frequency Response for Nonlinear Input-Output Maps' submitted to *Inter. J. Of System Science*.
- [15] B. Chanane, S. P. Banks, 1989, 'Rational Expansion for Nonlinear Input-Output Maps' submitted to *Inter. J. Of Control*.
- [16] W. Greub, 1978, **Multilinear Algebra**, Springer Berlin-NewYork, 2nd Edition.
- [17] A. J. Krener, 1975, 'Bilinear and nonlinear realizations of input-output maps', *S.I.A.M. J. Cont. & Optim.* 13 pp 827-834.
- [18] J. T. H. Lo, 1975, 'Global bilinearization of systems with control appearing linearly', *SIAM J. Cont. & Optim.* 13 pp 879-885.
- [19] H. Takata, 1979, 'Transformation of a nonlinear system into an augmented linear system', *I.E.E.E. Trans. Auto. Cont.*, **24** pp 736-741.
- [20] M. Takesaki, 1979, **Theory Of Operator Algebras I**, Springer-Verlag, New-York.